

Strategy

TWO CHANNEL PREAMP & OVERDRIVE

TONE

A high/low-pass filter network. At 1, lows are emphasized and highs are rolled off. At 10, highs are emphasized and lows are rolled off.

VOLUME

In Preamp Mode, Volume sets the overall output level. At higher settings, the circuit will begin to distort naturally. When in Overdrive Mode, Volume sets the gain level of the overdrive signal, which works in tandem with the internal trim pot.



PREAMP
MODE



OVERDRIVE
MODE

MODE SWITCH


Toggles between Preamp and Overdrive modes, indicated by the bypass LED.

SMART BYPASS™

A tap of the footswitch will engage the pedal as normal, while holding down the footswitch will activate momentary mode. The design of our relay based bypass network allows for the signal to pass through unaffected, should the pedal lose power.

MOMENTARY DIP SWITCH

When set to "ON", our SMART BYPASS™ system is engaged. To turn this off, simply switch the DIP down to the "1" position. Strategy comes factory set with momentary mode ON.



INTERNAL GAIN POT

In Overdrive Mode, the internal pot controls the overall saturation of the overdriven signal. Strategy comes factory set with the pot at 50%.

Clockwise = HARDER
Counter = SOFTER



IN/OUT: 1/4" Inst. Cable

POWER CONSUMPTION: ☹☹☹ @ 9V: 40mA | @ 18V: 40mA

We recommend using an isolated power supply. The Strategy has internal polarity protection. Daisy chained power supplies are not recommended.